

// Mobile printing from your iPad® and iPhone®

The universal, mobile printing solution from SEH has been developed for professional business use. It combines innovative hardware and software in one compact device: simply print all your documents, graphics and pictures straight from your iPad® and iPhone®.

With primos you do not need an AirPrint™ printer nor a desktop computer to act as a print server. primos will save you lengthy configuration, driver installation, and a multitude of printer applications. It doesn't matter which printer you have: once primos has been connected to your company network, you are ready to print. Manufacturer-independent, easy and absolutely secure through authentication and point-to-point encryption.



// For up to 10 printers.

// No additional apps needed.

// No need to print to a cloud.

■ Made
■ in
■ Germany

// Areas of Application

- Architecture
- Medicine
- Creative offices
- Law offices
- Field work
- For all those who need to print from their iOS® devices

// Data Security

In order to ensure data security and protection, primos administrators can define users and user groups using directory services. Supported directory services include: Microsoft® Active Directory® and OpenLDAP™. Administration and maintenance of primos is extremely simple with the user-friendly web interface.

// Benefits

Secure.

- Secure data encryption
- Authentication
- Local data administration (no cloud)

Convenient.

- Native iOS® compatibility
- Manufacturer-independent
- Smart Printer Setup
- Time-saving
- User-friendly
- Easy

**PATENT
PENDING**

Professional.

- AirPrint™ compatible user administration
- Functions over sub-networks (Wide-Area Bonjour®)
- Directory services support (Microsoft® Active Directory®, OpenLDAP™)

// Technical Specifications

Interfaces and Network Connectors

- 1 × RJ-45 (IEEE 802.3; 10BaseT, 100BaseTX, 1000BaseT)
- 1 × USB 2.0 (type A connector)

Configuration and Management

- SEH primos App: Microsoft® Windows (Windows 7, Windows 8, Windows 10), Apple® (OS X® 10.7.x–10.11.x)
- Primos Web Control Center (monitoring, configuration, administration, firmware updates, etc.)
- Driver management
- Smart Printer Setup (registered for a patent in Germanyw)

Supported Protocols

- TCP/IPv4 and IPv6:
DHCP, TCP, UDP, ICMP, IGMP, TFTP, HTTP, HTTPS, Zeroconf, DNS, SLP, SNMP, SSL/TLS, LDAP, Bonjour®, etc.

Security

- Encryption: SSL 3.0–TLS 1.2, HTTPS, IPP Secure, AirPrint™ Secure, etc.
- Authentication: 802.1X (EAP-MD5, EAP-TLS, EAP-FAST, EAP-TTLS, PEAP)
- Device & port access control
- Certificate management: self-signed certificate, certificate request, CA certificate, PKCS#12 certificate
- Password control

Supported Directory Services

- Microsoft® Active Directory®
- OpenLDAP™ (Apple®/Linux)

Supported iOS® Devices

- All iOS® devices from iOS® 4.2:
 - iPhone® (from 3GS)
 - iPad®
 - iPod touch® (from 3rd generation)

Supported Printers (simultaneously connect up to 10 printers)

- Network printers (LAN or WLAN) supporting at least one of the following protocols:
 - IPP
 - IPP Secure
 - LPD
 - Socket Printing (JetDirect™ Printing)
- USB printers

Supported Languages

German, English, Japanese

Tests (Notifications)

- CE: EN55022:2010 Class B, EN55024:2010, EN 50581:2012
- FCC class A
- VCCI class A
- ROHS

Power Supply

- External power supply
- Output: 5 V 2 A
- Input: 100–240 V ~

Operating Environment

- Temperature: 5–40 °C
- Relative humidity: 20–80 %

Dimensions (length, width, height)


108 × 108 × 33 mm

Weight

230 g

Order Number

M07010



SEH Computertechnik GmbH

Suedring 11 | 33647 Bielefeld | Germany

Phone: +49 521 94226-29 | Fax: +49 521 94226-99 | Support: +49 521 94226-44

Email: info@seh.de | Web: www.seh-technology.com

primos.seh-technology.com