

Product Highlights

Easy expansion

Quickly add seven USB 2.0 ports to any PC, allowing you to connect more peripherals with ease.

Sync and charge your iPad

Can be used with the free Windows utility to charge and sync your iPad at the same time.

Compact and portable

Fits easily into any bag for travel and can still function as a USB hub when without a power adapter.



DUB-H7

7-Port USB 2.0 Hub

Features

Connectivity:

- Seven USB 2.0 ports
- Backwards compatible with USB 1.1

Fast Charge Mode:

- Two USB ports for fast charging high-power mobile devices such as an iPad
- Does not require a PC to charge devices
- Windows app for syncing and charging an iPad at the same time

Easy To Use

- Plug and play
- Sleek, compact design
- Works on Windows, Mac, and Linux PCs

D-Link's DUB-H7 7-Port USB 2.0 Hub provides an easy way to add seven USB 2.0 ports to your notebook or desktop computer. In Fast Charge Mode, the hub's two black ports provide an increased charging current of 1.2 A to effectively charge high-capacity batteries like that of the iPad[®]. This means you can charge devices like iPads while also connecting additional USB devices like digital cameras, hard drives, mice, keyboards, printers, scanners, and many other peripherals.

Add Seven USB 2.0 Ports to Your Computer

With the DUB-H7 7-Port USB 2.0 Hub, you can conveniently add more USB 2.0 ports to any computer. Now you can connect up to seven more USB peripheral devices – such as digital cameras, printers, external hard drives, mice, keyboards, flash drives, and tablet computers – to your notebook or desktop computer. USB 2.0 technology supports data rates of up to 480 Mbps, which means that you can enjoy faster transfer speeds compared to previous USB standards.

Fast-Charge Your Devices

The DUB-H7 features two black Fast-Charge ports that are designed to provide an increased charging current of 1.2 A to connected devices when the DUB-H7 is in Fast Charge Mode. This makes it perfect for charging power-hungry mobile devices like the iPad, as these devices have high-capacity batteries that require higher charging currents to recharge quickly and effectively. The DUB-H7 does not require a PC to charge your devices, so you can take it with you on the road and leave your mobile device chargers at home.

Sync and Charge Your iPad at the Same Time

Normally, when syncing an iPad with a PC, you cannot charge the iPad at the same time. The DUB-H7 lets you do both, allowing you to back up your iPad while giving it a full charge at the same time. Simply install the Windows utility available on the D-Link website to enable your DUB-H7 to sync and charge simultaneously.

Plug and Play

Simply plug in the power adapter and connect the DUB-H7 to any PC. It's that easy - no drivers or software installation is required. Now you can connect up to seven additional USB devices to your laptop, notebook, or desktop computer.

Take It with You Anywhere

The DUB-H7 is designed to fit into any notebook bag, and the compact size of the device will allow you to conveniently carry it with you wherever you go. Experience the freedom and convenience of portability and expandability with the D-Link DUB-H7 7-Port USB 2.0 Hub.

Technical Specifications

Standards

Standards	<ul style="list-style-type: none"> • USB specification version 2.0 (data rates of up to 480 Mbps) • USB specification version 1.1 (data rates of up to 12 Mbps) 	<ul style="list-style-type: none"> • OHCI • UHIC • EHCI
Interfaces	<ul style="list-style-type: none"> • 7 downstream USB Type A (female) ports (including 2 Fast Charge ports) 	<ul style="list-style-type: none"> • Upstream USB Type B (female) port
Connectivity Rules	<ul style="list-style-type: none"> • Up to 127 devices • Up to five cascaded hubs 	<ul style="list-style-type: none"> • Maximum cable length between each hub: 5 m
Minimum System Requirements	<ul style="list-style-type: none"> • Windows 7 / Vista / XP • Mac OS 9.0 or above 	<ul style="list-style-type: none"> • Linux
Diagnostic LEDs	<ul style="list-style-type: none"> • Standard Mode (blue) 	<ul style="list-style-type: none"> • Fast Charge Mode (green)
Supplied Charging Current ¹	<ul style="list-style-type: none"> • Standard Mode: <ul style="list-style-type: none"> • 0.5 A on all seven front ports 	<ul style="list-style-type: none"> • Fast Charge Mode: <ul style="list-style-type: none"> • 0.5 A on all five white ports • 1.2 A on both black ports
Power Input	<ul style="list-style-type: none"> • 5 V / 3 A DC 	

General Specifications

Temperature	<ul style="list-style-type: none"> • Operating: 0 to 40 °C (32 to 104 °F) 	<ul style="list-style-type: none"> • Storage: -20 to 70 °C (-4 to 158 °F)
Humidity	<ul style="list-style-type: none"> • Operating: 10% to 90% non-condensing 	<ul style="list-style-type: none"> • Storage: 5% to 95% non-condensing
Dimensions (L x W x H)	<ul style="list-style-type: none"> • 100 x 57 x 23 mm (3.94 x 2.2 x 0.9 inches) 	
Weight	<ul style="list-style-type: none"> • 85 g (0.19 lbs) 	
Certifications	<ul style="list-style-type: none"> • FCC • CE • C-Tick 	<ul style="list-style-type: none"> • VCCI • IC • RoHS

Order Information

Part Number	Description
DUB-H7	DUB-H7 7-Port USB 2.0 Hub

¹ It is recommended that the total combined power draw not exceed 2.4 A or 12 W

Updated 03/23/12